

Included in the Box

- High Power MegaFi Router
- Antennas mounted on top cover (3x cellular, 2x Wi-Fi, and 1x GPS connections)
- Battery
- Fan
- Power Adapter
- Quick Start Guide

The SHIELD MegaFi High Power User Equipment (HPUE) paired with a specially designed Band 14 antenna puts everything in one case for the maximum high power user equipment experience. For set up, follow these steps.

1 Prerequisites

Ensure you or the distributor sending you the **MegaGo** have done the following:

- Activated the FirstNet SIM, which is included in the **MegaGo**
- Made note of the pertinent numbers located on the inside case panel (IMEI, Serial Number, SSID/Password, etc.)

2 Power Up

Before powering on, open the vent and fan caps on the sides of the unit. To power on, press and hold the **power button** located in the bottom left corner until the **LED indicator** lights up green. Wait for the unit to fully power up, which, in most instances will occur within three minutes.

3 Connect to Wi-Fi

The factory generated Wi-Fi SSID, authentication mode, and **password** are provided on the label inside the case. You can also **scan the QR code** on the label to automatically connect to Wi-Fi. The SSID will be present within three minutes of power up as noted above.

Note: It is possible to "hide" the SSID in the configuration, so if you have hidden your SSID, it will not be available. If this occurs and you cannot access the router Wi-Fi, then you will need to plug into the Ethernet port on the side of the case to access the router IP address as provided (or reset by you), or open the case and reset MegaFi using the reset button located in the front of the MegaFi unit.

4 In Use

Be sure the lid to the case is closed. This will generally provide the best connectivity, as the antenna in the case lid is designed to operate with the lid closed. Once the unit is operating and the lid is closed, please set "face up" as indicated on the outside of the case.

5 Power Recharge

To recharge the case, remove the power cord from the slot inside the case and plug it into the DC power port located on the left side of the case. Turn the power off before charging. If you need further help, please see more information at <https://nextivityinc.com/shield-megago/>

For more information scan the QR code or contact
Customer Support at support@nextivityinc.com

